

## 12898 And Or

Given  $A$  and  $B$ ,  $1 \leq A \leq B \leq 10^{18}$ , find the result of  $A|(A+1)|(A+2)|\dots|B$  and  $A\&(A+1)\&(A+2)\&\dots\&B$ .

| operator represents bitwise OR (inclusive)  
& operator represents bitwise AND

### Input

The first line of the input contains an integer  $T$  ( $T \leq 100000$ ) denoting the number of test cases. Each of the following  $T$  lines has two space separated integers  $A$  and  $B$ ,  $1 \leq A \leq B \leq 10^{18}$ .

### Output

For each input, print the output in the format, 'Case  $C$ :  $X$   $Y$ ' (quote for clarity). here  $C$  is the case number starting from 1,  $X$  is the result of bitwise (inclusive) **OR** of numbers from  $A$  to  $B$  inclusive and  $Y$  is the result of bitwise **AND** of numbers from  $A$  to  $B$ , inclusive.

For the exact input/output format please check the sample input/output section.

### Note:

| operator represents **bitwise OR**. A **bitwise OR** takes two bit patterns of equal length and performs the logical inclusive **OR** operation on each pair of corresponding bits. The result in each position is **1** if the first bit is **1** or the second bit is **1** or both bits are **1**; otherwise, the result is **0**. [Source: Wikipedia]

& operator represents **bitwise AND**. A **bitwise AND** takes two equal-length binary representations and performs the logical **AND** operation on each pair of the corresponding bits, by multiplying them. Thus, if both bits in the compared position are **1**, the bit in the resulting binary representation is **1** ( $1 \times 1 = 1$ ); otherwise, the result is **0** ( $1 \times 0 = 0$ ). [Source: Wikipedia]

### Sample Input

```
2
1 1
1 2
```

### Sample Output

```
Case 1: 1 1
Case 2: 3 0
```